

# Compatibility Matrix

## CommandCenter<sup>®</sup> Secure Gateway Release 5.4.0

*Please review the Release Notes for important release information. Consult the Quick Setup Guide, Deployment Guide, and Admin Guide for product setup instructions, implementation, and operations (note that there is a separate Quick Setup Guide for the virtualized version of CC-SG). Documentation is available on the Raritan website at [www.raritan.com/support/](http://www.raritan.com/support/)*

### I. Compatibility Matrix

*It is important to upgrade any listed Raritan products to the specified versions indicated below.*

#### CommandCenter Secure Gateway Firmware Information:

RARITAN PRODUCTS	FIRMWARE VERSION	SHIPS WITH
<b>CommandCenter Secure Gateway Physical and Virtual Appliance</b>	5.4.0	Multi Platform Client (MPC) 7.0.2 Raritan Serial Console (RSC) 3.0.0 Raritan Remote Client (RRC) 4.6.8 Raritan Console (RC) 2.7.20

The CC-SG firmware version can be located under Help→About Raritan CommandCenter.

Firmware versions of all Raritan devices can be verified by running a CC-SG Device Asset Report.

**CommandCenter Secure Gateway has been tested with the following Raritan product versions and with the supported client applications specified below.**

RARITAN PRODUCTS SUPPORTED		SUPPORTED FIRMWARE VERSIONS	
Product Name/Model	Part #	Current	Previous
Dominion KX II	DKX2-108, DKX2-116, DKX2-132	<b>2.5.0</b> <b>2.6.0</b>	<b>2.4.0</b>
	DKX2-216, DKX2-232		
	DKX2-416, DKX2-432, DKX2-464		
	DKX2-808, DKX2-832, DKX2-864		
Dominion KX	DKX116, DKX216, DKX232 DKX416, DKX432, DKX132, DKX464	<b>1.4.9</b>	<b>1.4.8</b>
Dominion KX II 101	DKX2-101, DKX2-101-v2	<b>3.5.0</b>	<b>2.0.40</b>
Dominion KX 101	DKX101	<b>1.1.1</b>	<b>1.1.0</b>
Dominion SX (Intel platform)	All Models * <sup>1</sup>	<b>N/A</b>	<b>N/A</b>
Dominion SX (MIPS platform)	DSX4, DSX8, DSXA16, DSXA32, DSXA48	<b>3.4.0</b>	<b>3.3.0</b>
Dominion KSX II	DKSX2-144, DKSX2-188	<b>2.6</b>	<b>2.3.5</b>
Dominion KSX	DKSX440, DKSX880	<b>3.6.0</b>	<b>3.24</b>

RARITAN PRODUCTS SUPPORTED		SUPPORTED FIRMWARE VERSIONS	
Product Name/Model	Part #	Current	Previous
Dominion PX* <sup>2</sup>	DPCSxxx, DPCRxxx, DPXSxxx* <sup>3</sup>	1.5.7	1.5.4
Dominion PX2* <sup>4</sup>	PX2-xxxx	N/A	N/A
Power IQ	PWIQxxx	4.0.2	3.1.3
PCR Power Strips	PCR8, PCR12, PCR18, PCR20	N/A	N/A

1. SX Intel models are not supported.
2. Dominion PX firmware versions listed in this Compatibility Matrix are required for direct connectivity to CC-SG via IP modes. For Dominion PX firmware versions required in 'managed power strip' mode (when Dominion PX connection to a Dominion device via a power CIM or power cable) refer to the documentation of the Dominion device managing the PX for special instructions.
3. xxx represents 3 alphanumeric values that would be different for each model in the product category.
4. PX2 management requires Raritan's Power IQ. Please refer to Power IQ for supported versions

#### Miscellaneous Applications & Interfaces:

OTHER PRODUCTS SUPPORTED	SUPPORTED VERSIONS
VMware™ vSphere, ESXi	4.1.0, 5.0.0, 5.1.0
VMware ESX	4.1.0
VMware Remote Console	Version supported in VMware distribution
iLO3	1.26
iLO2	2.07
iLO	1.94
Integrity ILO2	F.02.26
iPad / iPhone	5.1, 6.0
DRAC4	1.75
DRAC5	1.60
DRAC6	1.80
RSA II	1.14 (using Windows)
IBM IMM	1.x
IPMI	1.5, 2.0
UCS KVM	2.0
Telnet	1.0
RDP	1.1
Microsoft RDP	5.2.3790.0
VNC	1.0.1 ( Tight VNC )
SSH	1.0.1
Flexera License Server	Imgrd and lmadm 11.8, running on 32 bit server Note: CC 5.4.x is the last release to support the license server. Only the "Not Served" mode (no Flexera license server) will be supported in future releases.

The CC-SG Admin Client (Java) and CC-SG Access Client (HTML) are supported in the following environments:

CLIENT PLATFORMS	SUPPORTED BROWSERS	SUN JRE <sup>*1</sup> SUPPORT
Windows 8	IE10, FF19	1.7 .0_21
Windows 7	Internet Explorer 8.0, 9.0, 10.0 Firefox <sup>*3</sup> 12 through 20	1.6.0_10 thru 1.6.0_43 <sup>*6</sup> 1.7.0_4 thru 1.7.0_21 <sup>*4</sup>
Windows 2008 Server	Same as above	Same as above
Windows Vista <sup>*2</sup>	Same as above	Same as above
Windows XP <sup>*2</sup>	Same as above	Same as above
Windows 2000	Same as above	Same as above
SUSE 11	FF 16 through 20	Same as above
Solaris 10	Same as above (no IE)	Same as above
Fedora 16,18	FF 16 through 20	Same as above
MacOS 10.6 (Snow Leopard), 10.7 (Lion), 10.8 Mountain Lion	Same as above (no IE) Safari 6 <sup>*5</sup>	Same as above
Red Hat EL 4, 5	Firefox 3.5 – 4.0	Same as above

1. CC-SG Release 5.4.0 is compatible with these specific versions of Sun JRE and is not supported for use with other versions. Unsupported versions include: 1.7.0\_11 and 1.7 update 9-bo5. Sun JRE's can be found at <http://java.sun.com/j2se/>.  
  
If using Windows and using the client applet, JRE will only work with Windows 32 bit. See <http://java.sun.com/javase/6/webnotes/install/system-configurations.html> for Java support information.
2. Both 32 and 64 bit OS editions are supported
3. The CC-SG Administrators Client cannot be launched in an IPv6 network when using Firefox 6, 7, 8, 9, 10, 11, or 12. This is due to a certificate bug caused by Firefox. A workaround is available that includes installation of a user certificate. Details are provided in the Administrators Guide. Please contact Raritan Tech Support for assistance.
4. If using JRE 1.6, we recommend 1.6 update 43, if using JRE 1.7, we recommend 1.7 update 21.
5. Some issues can be resolved by using FF instead of Safari
6. CC-SG Release 5.4.x will be the last release(s) to support JRE 1.6 (Java 6). Post Release 5.4.x, only JRE 1.7 (Java 7) will be supported.

CLI access to CC-SG is supported in the following environments:

CLIENT APPLICATIONS	SUPPORTED VERSIONS
SSH	PuTTY version 0.58 or later. OpenSSH